

MADE IN INDIA

 **SUNRIDE**[®]
SOLAR



**MOST ADVANCED TECHNOLOGY
MPPT BASED PCU**

**FORGET THE FEAR OF
DARKNESS WITH
ULTRA**

 **UNNY PLUS**
SOLAR HYBRID UPS
POWER CONDITIONING UNIT



**1700
24V**



**30% MORE
EFFICIENT**



**CHARGING
FROM MAINS
UPTO 90 VOLTS**



**LCD
DISPLAY**



**ADVANCED DSP
CONTROLLER FOR
EFFICIENT WORKING**

www.sunride-solar.com

PARAMETERS	MODELS
iModel	1700VA/24V
No Load Current	≤ 2.4A
Output Voltage @ No Load	≤ 240VAC @24.6VDC
Battery Current @ Full Load	52A ±2A
Over Load Alarm	54A ±2A
Battery Low Alarm	21.2 ±0.2V
Battery Low Shutdown	20.8 ±0.2V
Short Circuits Protection	Yes
Inverter Output Frequency	50 ± 0.1 Hz
	UPS MODE
Mains Input Volatge Range	170V To 265V
Mains AC Low Cut	170VAC ±5VAC
Mains AC Low Cut Recovery	180VAC ±5VAC
Mains AC High Cut	265VAC ±5VAC
Mains AC High Cut Recovery	250VAC ±5VAC
Maximum Change Over Time	<10msec
	W-UPS MODE
Mains Input Volatge Range	90V To 295V
Mains AC Low Cut	90VAC ±5VAC
Mains AC Low Cut Recovery	110VAC ±5VAC
Mains AC High Cut	290VAC ±5VAC
Mains AC High Cut Recovery	280VAC ±5VAC
Maximum Change Over Time	<20msec
	CHARGING MODE
Charging Current@220VAC	15.0 ±2A
Boost Voltage(Tub. Mode)	28.8V ±0.2V
Boost Voltage(LA. Mode)	27.6V ±0.2V
Boost Mode(Enable Tub. Mode)	30.0V ±0.2V
Boost Mode(Enable LA Mode)	29.6V ±0.2V
Float Volatge	27.2V ±0.2V
Short Circuit	Yes
	PROTECTION
Battery Low Cut Off	1 Time
Over Load (Auto Retries)	4 Times
Short Circuits (Auto Retries)	3 Times
Over Temperature	3 Times
Battery Over Charge	Yes
Input Protection	Yes (Mains MCB Trip in Case of Short Circuit in Mains Mode)
Rating	24V-50Amp.
Input PV Volatge Max. Voc	50V
Maximum Solar Arrey Power	1000W
Maximum PV Modules	330W
Type of Control	Micro Controller
Type of Solar Charger	PWM
Efficiency Of SCC	>90%
PV Volatge High Protection	60V
PV High Current Protection	55Amp.
	DISPLAY
16X2 LCD	Mains Voltage, Output Voltage, Battery Charging, Battery Charged, Solar Voltage, Solar Current, Main MCB Trip and all protection alert with it's remedy.
20X4 LCD	
LED INDICATIONS	Mains On, Charging, On, UPS, On, Battery Low, Overload